





# Temperature Detection Facial Recognition Device



-   
**Infrared Precise  
Temperature Detection**
-   
**Fast Live  
Body Detection**
-   
**Multiple Mode  
for Face Registration**
-   
**Time Attendance  
and Access Control**

**Features**

- Body Temperature Detection
- Detection Minimum Unit: 1.0°C
- Abnormal Temperature Automatic Alarm
- Wearing Mask Identification
- Abnormal Temperature Warning
- Binocular Live Detection

Is working for daily face identification attendance and access control monitoring by forehead temperature detection. Which can be widely used in the place like Hospital, Community, Park, Campus and different gathering zones etc.

**Infrared Temperature Detection Sensor**

Precisely detect temperature, binocular seizing and live face identification

**High Capacity user and Logs**

3,000 Face and 1,000,000 Logs



Specification	
CPU Processor	4 Core 1.2G
Temperature Detection Distance	0.5meter
Temperature Detection Error	0.5°C
Temperature Detection Minimum Unit	0.1°C
RAM	4G DDR3
ROM	32G eMMC
Camera	200W Pixel HD Color Camera 100W Infrared Camera
Fill Light	Highlight LED Fill Light Dual Infrared High Power Fill Light
Display Screen	12.7CM (5) Electronic Capacity Touch Screen
Screen Resolution	854*480
Keyboard	Touch Virtual Keyboard
Communication Method	TCP/IP, WiFi, USB Pen Drive
FRR	<=0.1%
FAR	<=0.001%
Product Size	154x152x22mm
Power Supply	DC 12V, 2A
Working Temperature	-15°C ~ 60°C
OS	LINUX System
User ID Capacity	3,000
Face Capacity	3,000
User Record Capacity	1,000,000
Identification Type	Dynamic Face Recognition, Password, Face Recognition and password
Face Recognition Mode	1:1, 1:N
Identification Display	Person Name & Number
Face Recognition Time	< 0.2s
Intelligent Function	Infrared Live Person Identification Detection
Face Recognition Display	Purely Dynamic Facer Recognition: 0.5~3m Infrared Live Movement Detection: 0.5~1.5m
Door Sensor	Support
Alarm Output	1 set
Relay Output	1 set
RS-232 Output	1 set
RS-485 Output	1 set
U-Disk Output	1 set
Exit Switch	1 set
Wiegand Input	1 set WG26/34 Input
Wiegand Output	1 set WG26/34 Output