Secureye

DATASHEET

16 CH XVR
(4 MP)



KEY FEATURES

- 16Ch Video Recording
- G.711A Audio Compression
- 16Ch BNC Video Input
- 2Ch RCA Audio Input

With Smart Analytics

CE FC RoHS COMPLIANT

Supported Browser

Firefox IE Chrome Safari

SPECIFICATION	S-16C2S-4M
Operating System	Embedded LINUX
Penta - Bird Technology	Supports AHD / HDCVI / HDTVI / CVBS / IP
Video Compression	H.264+, H.264
Video Recording	Full 16ch AHD
Display Quality	Support 4MP/3MP/1920*1080, 1280*720, 1440*900, 1280*1024, 1024*768
Features	Auto AWB, Mirror, Reverse, No Colour, WDR, Corridor
Playback Quality	4MP/3MP/1080P/720P/D1
Encode / Decode Capacity	16*4MP / 16*4MP
Motion Detection	192(16*12) detection area: multi-level sensitivity
Audio Compression	G.711A
Recording Mode	Manual/alarm/dynamic detection/Timing
Play Back	1~4 channel playback, Local 4*4MP mode
Recording Storage	Local Hard disk, Network
Backup Mode	Network Backup, USB Hard Disk
Video Input	16ch BNC
Video Output	1ch VGA, 1ch HDMI
Audio Input	2ch RCA
Audio Output	1ch RCA
Net Interface	RJ45 10m/100m Adaptive Ethernet Port
PTZ Control	1 RS485; Support Multi PTZ Protocol
USB Interface	2 USB Interface
HDD Interface	2 SATA Up to 6TB each
Smart Alert	No Video, HDD Error, HDD faulty, Motion Detection
Smart Analytics	Virtual fencing, Restricted Area, Defence Zone
Power Supply	12V DC
Working Temperature / Humidity	-10°C ~ 55°C / 10% ~ 90%

www.secureye.com

Intelligent 5 In 1 XVR

with SMART ANALYTICS


Get Alert on any of the below situations




Network Disconnection




HDD Full



HDD Error



Motion Detection



No Video

Supports
H.264+
TECHNOLOGY.
This Increases
30% ~ 40%
Storage Capacity
as Compare to H.264

Supported by All Channels

Smart Analytics Alert



Virtual Fencing



Defence Zone



Restricted Zone

Smart Analytics Supported

4 Channel DVR	8 Channel DVR	16 Channel DVR
1 Channel	2 Channel	2 Channel

On Alert the Screen will Pop-up

Get All Alert on Email
&
Mobile APP



Available on the App Store

Google play